



ITX-E2011

Mini-ITX from Inter-Tech - modern, stylish and practical. The E-2011 is especially evident by the bright blue stripes in the piano lacquer-like front panel. In addition, it has a hidden external power connector under a small flap, for e.g. a DVD drive.

Mini-ITX systems are very energy-saving, so that the external 60W Power Supply is sufficient to build up a powerful ITX system. If it should be a little more power, you can also use an optional 120W Power Supply, cause the internal circuit board is able to process an input voltage of up to 120W.

An intelligent interior layout allows, despite the small space, an easy installation of all components. Front connectors like 2x USB 2.0 and HD-Audio round out the features.

Specifications

Motherboard	ITX
Drive Bays	2.5" internal: 1
Front Connectors	USB 2.0: 2 Microphone: 1 Headphone: 1 External SATA-Data connector: 1 External Molex connector: 1
Cooling System	Side: 1x 40mm
Power Input	For 12V plugs with dimensions of 5.5x2.5x10.7mm
Maximum CPU cooler height	40mm
Maximum graphics card length	-
Packing Units	Shipping Unit: 1 Piece Packing Unit: 8 Pieces
Guarantee and Warranty	Case 24 Months Warranty Power Supply 24 Months Guarantee
Article Number	88881142
EAN-Code	4260133124714
Scope of Delivery	External 60W Power Supply Circuit board max. 120W S-ATA data cable Cable ties Screw Set Stand Rubber feet (adhesive)
Features	External 60W Power Supply USB 2.0 and Audio connectors internal as block connector HD-Audio
Optional Accessories	VESA Bracket (Art. 88885230) External 90W PSU (Art. 88882098) External 120W PSU (Art. 88882103)

Dimensions and Weight

	Cage	Case	Package
Height	60mm	60mm	265mm
Width	190mm	190mm	280mm
Depth	230mm	250mm	130mm

Weight (net): 1.48Kg
Weight (gross): 2.26Kg

DC/DC-Platine:

Connectors	Quantity	Max. Length
Mainboard 20+4Pin	1x	-
P4 12V 4Pin	1x	-
IDE 4Pin	1x	-
S-ATA	1x	-
Floppy	1x	-

DC Output	Output Voltage (V)	Max. Output Current (A)
+3.30 V	+3.30	10.0
+5.00 V	+5.00	10.0
+5.00 VSB	+5.00	2.0
+12.00 V	+12.00	4.5
-12.00 V	-12.00	0.15

Certification:

